Cinelex SKYFI

Simple Wi-Fi Control Of Any DMX Light

FULL CONTROL, NO WIRES

Wirelessly control any DMX-capable light fixture using Wi-Fi.

SIMPLE SETUP

SKYFI broadcasts a Wi-Fi signal for any smartphone, tablet or computer to connect.

WEB BROWSER UI

Includes a simple intuitive user interface - accessible from any web browser on the host device.

ART-NET PROTOCOL

Fully-Compatible with Wi-Fi/Art-Net control apps, such as Luminair.

USB-POWERED

Power SKYFI from any 5V USB source.











| Wireless Protocol | |
|---------------------------------|--------------------------------|
| Protocol | Art-Net |
| Operational Frequency | 2.4GHz |
| Range | 30m |
| Power | |
| Micro-USB | 5V |
| Power Consumption | 0.6W |
| Controls | |
| 1x "RESET" Button | Restart SKYFI |
| Connectors | |
| 1x DMX XLR 5-Pin Female | |
| 1x Micro-USB Power Input Female | |
| 1x Built-In Antennae | |
| LED Indicators | |
| 1x "ART-NET" LED | Art-Net Packet Activity Status |
| 1x "POW" LED | Power Input Confirmation |
| 3x Signal Strength LEDs | Signal Strength Indicator |
| Size (with Antennae) | |
| Weight | 49g |
| Dimensions | 60mm x 26mm x 38mm (L x W x D) |